

Firmware Modification Procedure:

WARNING:

- **Make sure that other Firewire devices are not connected except for the Pyro Drive Kit (alone) that is experiencing the problem.**
- **Make sure that the PC is freshly booted.**
- **Changes on the firmware other than this instruction intend WILL VOID the warranty and may malfunction.**

Before you start

- Please ensure that you have Winzip installed in your computer. The software is available for free from www.winzip.com
- Make sure that other Firewire devices are not connected except for the Pyro Drive Kit (alone) that is experiencing the problem.

Installation:


Open the file Drive Kit Mod.zip and run "Setup.exe", proceed with the installation. After the installation restart the computer.

Starting and running the Application:

- Click on "Start" and click on "Run"
- Type down "C:\Program Files\Oxford Semiconductor\OXFW900 Uploader " and press

OK


- On the new window, open the icon called "FWUpload" and you will see the window like the one below (fig1) and follow the instructions in the boxes which are in order.



(Fig 1)


NOTE: Disregard other info that you see in the pictures such as Firmware Rev, Flash Device, etc. it can be different as what you have or see.

See next page for further steps



2.) Click here (Advanced) to proceed.

(Fig2)




3.) Add a check mark next to "Detect drives with non-std. signature"

4.) When the check mark is added, click "OK"

(Fig 3)

See next page for further steps



(fig 4)

5.) It will take you back to this window, now to make changes, click on "Upload"

- a. When the upload is finished or the bottom of the screen says "Ready", disconnect the Pyro Drive Kit and close the application
- b. Turn off the Pyro Drive Kit from the power for 5 seconds
- c. After 5 seconds. Turn it back on
- d. Reconnect the firewire connection. Upon reconnection, proceed now with your intended use of this drive kit as it should operate normally.

Issues/Notice:

- The Pyro Drive Mode selector may not show the vendor field correctly, this is normal after the firmware updater is installed
- There is no need to use the Pyro Drive Mode selector to configure the Pyro Drive Kit that has a firmware dated October 2000 or later.
- Other modifications to the firmware than this document suggested will void warranty and may cause the drive kit to malfunction.